

2-in-1 Emergency Light

ESAH211



The *Energizer*® 2-in-1 Emergency Light is a versatile area light and directional light in one compact and highly reliable product. Designed for both outdoor and indoor use, its brightly colored finish and reflective panels ensure that it is easy to find in emergency situations. The area light mode provides broad, diffused light to illuminate larger spaces while maintaining an extremely long runtime and a red flashing light for signaling in emergency situations. The directional light mode provides a concentrated, direct light with a lengthy runtime and an excellent beam reach. The magnets around the lens allow handsfree use while signaling which is perfect for auto emergencies. Tough by design, the *Energizer*® 2-in-1 Light is durable and water resistant.

Lumens	Runtime	Beam Distance	Drop	Water Ingress
<p>FL1 STANDARD 90 LUMENS</p>	<p>FL1 STANDARD 38h</p>	<p>FL1 STANDARD 65m</p>	<p>FL1 STANDARD 1m</p>	<p>FL1 STANDARD IPX4</p>



DESIGN BENEFITS
<ul style="list-style-type: none"> ✓ Combined area and spot modes in one product ✓ Durable construction ✓ High-visibility reflective panels ✓ Red flashing for signaling ✓ Magnets around the lens for handsfree use ✓ Floats

PERFORMANCE BENEFITS
<ul style="list-style-type: none"> ✓ LED technology ✓ Long runtime in spot mode ✓ Light floats in water

LIGHT AND POWER SOURCE
<ul style="list-style-type: none"> ✓ Features LED technology ✓ Operates on 2 AA batteries

BATTERY SPECIFICATIONS	
Battery Type	ENR Max Alkaline
Battery Size	AA
Number of Cells	2

PRODUCT SPECIFICATIONS	
Weight:	86 Grams / 2.99 Ounces
Dimensions:	170 mm x 58 mm x 58 mm 6.69" x 2.28" x 2.28"

BATTERY PERFORMANCE			
Modes	Lumens (lm)	Runtime (h)	Beam Distance (m)
Directional Spot-On	90	38	65
Area-On	90	24	6

ELECTRICAL CHARACTERISTICS	
Nominal Power Consumption:	0.75 W
Batteries:	2 AA Energizer E91 3.0V dc
LED Specifications:	LED 3.0V cc / 250 mA

DISCLAIMERS
<p>Tested according to ANSI/NEMA FL1 Standards.</p> <p>This device complies with part 15 of the FCC Rules. Operation is subject to the following two conditions: (1) This device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.</p>

Other Modes
High, Area, Red Flash (1.5Hz)

CERTIFICATES AND COMPLIANCE
EMC, EN62471, FCC



Publish Date: 4/1/2024

Before using your flashlight, please read all instructions and cautionary marking on the package and the light. This datasheet contains information specific to products manufactured at the time publication. Contents do not constitute a claim or warranty.

©2020 Energizer

OPERATING INSTRUCTIONS

1. Press on/off button to turn on.
2. Press 1x for directional light.
3. Press 2x for area light.
4. Press 3x for flashing red area light.
5. After 2 seconds in a mode, next press will be off.

BATTERY CHANGING INSTRUCTIONS

1. Unscrew lens ring to access batteries. Follow diagram on light body for battery orientation