

[Download Instructions \(Americas\)](#)
[Download Instructions \(Rest of World\)](#)

Universal Charger

MAXIMIZES PERFORMANCE

- Helps batteries retain capacity by preventing damage from overcharge



ENSURES FULL CHARGE

- Charges batteries to 100% capacity



EASY TO USE

- LED lights indicate when batteries are charging



VERSATILE

- Charges AA, AAA, C, D and 9V NiMH batteries



LED Functions/Status

LED Functions: When AAA/AA batteries are placed in the charger
 Green LED on: Charging
 Green LED off: Charge completed, or no battery inserted
 Green LED flashing: Alkaline protection or short circuit protection

Before Using Your Charger:

Please read all instructions and cautionary markings on the battery charger, batteries, and device.

Best used with Energizer® NiMH batteries.

Product Detail:

Designation: Universal Charger

Model: CHFC3

Color: Black

Charging Capability: AA/AAA/C/D/9V

Battery (NiMH)	Capacity (mAh)	Estimated (time)
AA	1300-2000	3-4 hrs
AA	2000-2300	4-5 hrs
AAA	500-800	2-3 hrs
C/D	2500	5 hrs
9V	175	8 hrs

Shutoff Mechanism: Delta V Detection: 5mV per cell for "AA-AAA-C-D"

Timer Control: 2 or 4 "AA-C-D": 5 hrs

2 or 4 "AAA": 3.5 hrs

1 or 2 "9V": 8 hrs

Charging Current: "AA-C-D" 650mA

"AAA" 400mA

"9V" 30mA

Trickle Charge: None

Input Rating: 100-240VAC, 50-60Hz, 6W

Typical Weight: 322 grams

Dimensions (mm): 48 x 199 x 107 (H x L x W)

Safety Features: Short Circuit and Reverse Polarity Protection

Primary Battery Detection

Bad Battery Detection

Delta V Charging Cut Off

Safety Timer to Prevent Overcharge

Important Notice

This datasheet contains information specific to products manufactured at the time of its publication.

Contents herein do not constitute a warranty.